

# AQUA MASTER INLINE Y CONNECTOR

IP68 - 16A - 230V 50Hz  
3 - Pole screw terminals  
Min 0.75mm 3 core  
Max 4.00mm 3 core

## SAFETY

These instructions must be followed carefully to ensure the product is watertight and electrically safe.

- Before installation/maintenance ensure that the supply to the cable to be joined is switched off and the circuit fuses are removed or switched off.
- All wiring should be carried out by a competent person or a qualified electrician and should be fitted to IET 17th wiring regulations BS 7671:2008.
- The circuit **MUST** be wired into an approved Residual Current Circuit Breaker.
- Ensure the correct cable diameter used is within cable range stated on the packaging.

## INSTALLATION

### 1) Parts of the connector



# INSTALLATION (Continued)

## IMPORTANT

Wire and assemble the 'Y' end of the connector (A & B) before the straight end C.

In the event of replacing any of the cables you should always remove the straight end's nut, grip and yellow grommet first and replace and tighten them last.

Insert the brown wire into the terminal marked L  
Insert the Blue wire into the terminal marked N  
Insert the Green/Yellow wire into the terminal marked E

